

**2.8.1.18 File -> Properties - Statistics**

This tab shows the creation date of the circuit program and the last author.

**2.8.1.19 File -> Properties - comment**

In this tab, you can enter a description of the circuit program or notes relating to it. When you print your circuit program using the File → Print (Page 52) menu command, you can choose to print this comment on a separate printed page.

**2.8.1.20 File -> Properties - Modbus address space**

In this tab, you can view the mapping relationship between ModBus address and LOGO! resource.

| Type Name | LOGO! Resource | Modbus Address             | Direction | Unit |
|-----------|----------------|----------------------------|-----------|------|
| I         | 1 - 24         | Discrete input 1 - 24      | R         | bit  |
| Q         | 1 - 20         | Coil 8193 - 8212           | R/W       | bit  |
| M         | 1 - 64         | Coil 8257 - 8320           | R/W       | bit  |
| V         | 0.0 - 850.7    | Coil 1 - 6800              | R/W       | bit  |
| AI        | 1 - 8          | Input Register 1 - 8       | R         | Word |
| VW        | 0 - 850        | Holding Register 1 - 425   | R/W       | Word |
| AQ        | 1 - 8          | Holding Register 513 - 520 | R/W       | Word |
| AM        | 1 - 64         | Holding Register 529 - 592 | R/W       | Word |

**2.8.1.21 File -> Exit**

The Exit command closes LOGO!Soft Comfort

If you are editing a circuit program or project and have not yet saved it, LOGO!Soft Comfort prompts you about your project.

In diagram mode interface you can state which circuit programs are to be saved. Alternatively, you can exit LOGO!Soft Comfort without saving circuit programs. To do this, click **Close without saving**. In the network project interface, you can click **Yes** to save the project or click **No** to exit without saving it.



A quick way of closing LOGO!Soft Comfort without saving the data (Page 398)